Screw for bracket Plate Type E snap ring Panel mounting bracket (Standard) Operation on the panel front permits mounting. Holes for mounting bolts are not necessary. (Mountable panel thickness is 4 mm maximum.) Plug connector Clamp bolt Socket connector Seal With One-touch fittings Plug case Socket case Possible to use from vacuum (-100 kPa) to 1 MPa. Applicable to copper-free type (electroless nickel Irregular shape permits plated). Two types, with 10 and 20 connector tubes, are engagement in a proper position. available. Tubes of different sizes can be used simultaneously Metric size - ø3.2, ø4, ø6, ø8

Model

Number of connecting tubes		Tubing O.D.	Model	Weight	Color of release button
		ø3.2	10-KDM10-23		
40		ø4	10-KDM10-04	300 g	140.3
10	Metric size	ø6	10-KDM10-06		White
		ø8	10-KDM10-08	520 g	
		ø3.2	10-KDM20-23		
00	Metric size	ø4	10-KDM20-04	520 g	White
20		ø6	10-KDM20-06		
		ø8	10-KDM20-08	950 g	

Applicable Tubing Material

Tubing material		Polyurethane	
Tubing O.D.	Metric size	ø3.2, ø4, ø6, ø8	

Specifications

Air
-100 kPa to 1 MPa
1.5 MPa
-5 to 60°C (No freezing)
Fluorine grease
Class 5

Note) Do not use the S couplers with a leak tester or for vacuum retention because they are not guaranteed for zero leakage.



Principal Parts Material

Plug case, socket case		POM	
Plate, bracket		SPCC plated	
Plug connector, socket connector	Body	PBT, C3604BD electroless nickel plated (ø8, ø5/16)	
	Chuck	Stainless steel 304	
	Guide	PBT (ø8, ø5/16), Stainless steel 304	
	Collet, Release button	POM	
	Seal	NBR	
Clamp bolt, Screw for bracket, Cross-recessed round head screw		SWRM nickel plated	
Type E snap ring		Stainless steel 304	

Part No.

Number of connection	Tubing O.D.	Part no.		Color of release button
tubes	Tubing O.D.	Plug	Socket	Color of release buttori
	ø3.2	10-KDM10P-23	10-KDM10S-23	
10	ø4	10-KDM10P-04	10-KDM10S-04	
	ø6	10-KDM10P-06	10-KDM10S-06	
	ø8	10-KDM10P-08	10-KDM10S-08	White
20	ø3.2	10-KDM20P-23	10-KDM20S-23	VVIIILE
	ø4	10-KDM20P-04	10-KDM20S-04	
	ø6	10-KDM20P-06	10-KDM20S-06	
	ø8	10-KDM20P-08	10-KDM20S-08	


Mixed Sizes of Plug Connectors and Socket Connectors

The rectangular multi-connector permits connector exchange in any desired position, thus allowing use of different sizes of tubes.


Part No.

Connector	Tubing O.D.	Part no.	Color of release button	
	ø3.2	10-KDMP-23		
Plug connector	ø4	10-KDMP-04		
r lug connector	ø6	10-KDMP-06	White	
	ø8	10-KDMP-08		
	ø3.2	10-KDMS-23	vvriite	
Socket connector (with seal)	ø4	10-KDMS-04		
	ø6	10-KDMS-06		
	ø8	10-KDMS-08		

(1) Loosen the cross-recessed round head screws using a Phillips screwdriver to remove the plate from the case.



(2) After exchanging connectors in desired places, fix the plate to the case by using a Phillips screwdriver.



Air


Be sure to read this before handling.

How to Use

∖ Caution


1. Separation

Loosen the clamp bolt to separate the plug side from the socket side.




2. Connection

Put together the irregular faces for engagement and connect the plug case to the socket. After tightening the clamp bolt by hand, tighten it further with an Allen wrench (nominal width across flats: 4).




3. Panel mounting


1) Loosen 4 screws for bracket on the socket side using a Phillips screwdriver (JIS nominal No. 2) until the bracket touches the snap ring.



2) Shift the panel mounting bracket to the inside (move the screw for bracket in the longitudinal direction of the slot) and put the connector in the panel mounting hole. (Please refer to the panel mounting hole "Dimensions".)



3) After shifting the bolt for bracket to the outside, tighten the bolt by a Phillips screwdriver to fix the socket case.





4) Loosen the screw for bracket until the bracket touches the snap ring and shift the bracket to the inside to remove the connector from the panel.





Dimensions


10-KDM10











Made to Order

Please contact SMC for specifications in detail, dimensions and delivery.

■ Mixed tubing sizes

Please contact SMC when mixed tube size manifolds are required since it is Made to Order.